

# INSERT ARRANGEMENTS

## MR1-MP1 INSERT ARRANGEMENTS

MR1 & MP1 AVAILABLE INSERT ARRANGEMENTS				
ARRANGEMENT	CONTACT SIZE (AWG)			
	#23	#20	#16	#12
5-3	3	X	X	X
6-4	4	X	X	X
6-6	6	X	X	X
6-7	7	X	X	X
7-10	10	X	X	X
8-13	13	X	X	X
9-19	19	X	X	X
10-26	26	X	X	X
12-37	37	X	X	X
6-23	X	3	X	X
7-25	X	5	X	X
8-28	X	8	X	X
9-210	X	10	X	X
12-220	X	20	X	X
6-1	X	X	1	X
8-2	X	X	2	X
9-4	X	X	4	X
10-5	X	X	5	X
12-7	X	X	7	X
7-1	X	X	X	1
10-2	X	X	X	2
12-2	X	X	X	2
12-3	X	X	X	3
9-200	4	X	2	X
10-202	8	X	2	X
12-202	20	X	2	X
12-203	12	X	4	X
10-200	12	X	X	1
10-201	4	X	X	2
12-200	6	X	X	2
12-201	10	X	X	2
12-204	12	X	X	2
12-205	4	X	X	4

# MR2-MP2 INSERT ARRANGEMENTS

MR2 & MP2 AVAILABLE INSERT ARRANGEMENTS				
ARRANGEMENT	CONTACT SIZE (AWG)			
	#23	#20	#16	#12
5-3	3	X	X	X
6-4	4	X	X	X
6-6	6	X	X	X
6-7	7	X	X	X
7-10	10	X	X	X
8-13	13	X	X	X
9-19	19	X	X	X
10-26	26	X	X	X
11-31	31	X	X	X
13-37	37	X	X	X
16-55	55	X	X	X
17-85	85	X	X	X
19-100	100	X	X	X
21-130	130	X	X	X
6-23	X	3	X	X
7-25	X	5	X	X
8-28	X	8	X	X
9-210	X	10	X	X
13-220	X	20	X	X
16-235	X	35	X	X
17-241	X	41	X	X
19-255	X	55	X	X
21-269	X	69	X	X
6-1	X	X	1	X
8-2	X	X	2	X
9-4	X	X	4	X

MR2 & MP2 AVAILABLE INSERT ARRANGEMENTS				
ARRANGEMENT	CONTACT SIZE (AWG)			
	#23	#20	#16	#12
10-5	X	X	5	X
13-7	X	X	7	X
16-12	X	X	12	X
17-14	X	X	14	X
19-19	X	X	19	X
21-22	X	X	22	X
7-1	X	X	X	1
10-2	X	X	X	2
13-2	X	X	X	2
13-3	X	X	X	3
16-4	X	X	X	4
16-5	X	X	X	5
17-7	X	X	X	7
21-12	X	X	X	12
8-200	4	2	X	X
9-201	8	2	X	X
9-200	4	X	2	X
10-202	8	X	2	X
13-202	20	X	2	X
13-203	12	X	4	X
10-200	12	X	X	1
10-201	4	X	X	2
13-200	6	X	X	2
13-201	10	X	X	2
13-204	12	X	X	2
13-205	4	X	X	4

# MR3-MP3 INSERT ARRANGEMENTS

MR3 & MP3 AVAILABLE INSERT ARRANGEMENTS				
ARRANGEMENT	CONTACT SIZE (AWG)			
	#23	#20	#16	#12
8-4	4	X	X	X
8-6	6	X	X	X
8-7	7	X	X	X
9-10	10	X	X	X
10-13	13	X	X	X
11-19	19	X	X	X
12-26	26	X	X	X
13-31	31	X	X	X
15-37	37	X	X	X
18-55	55	X	X	X
19-85	85	X	X	X
21-100	100	X	X	X
23-130	130	X	X	X
8-23	X	3	X	X
9-25	X	5	X	X
10-28	X	8	X	X
11-210	X	10	X	X
15-220	X	20	X	X
18-235	X	35	X	X
19-241	X	41	X	X
21-255	X	55	X	X
23-269	X	69	X	X
8-1	X	X	1	X
10-2	X	X	2	X
11-4	X	X	4	X
12-5	X	X	5	X

MR3 & MP3 AVAILABLE INSERT ARRANGEMENTS				
ARRANGEMENT	CONTACT SIZE (AWG)			
	#23	#20	#16	#12
15-7	X	X	7	X
18-12	X	X	12	X
19-14	X	X	14	X
21-19	X	X	19	X
23-22	X	X	22	X
9-1	X	X	X	1
12-2	X	X	X	2
15-2	X	X	X	2
15-3	X	X	X	3
18-4	X	X	X	4
18-5	X	X	X	5
19-7	X	X	X	7
23-12	X	X	X	12
10-200	4	2	X	X
11-201	8	2	X	X
11-200	4	X	2	X
12-202	8	X	2	X
15-202	20	X	2	X
15-203	12	X	4	X
12-200	12	X	X	1
12-201	4	X	X	2
15-200	6	X	X	2
15-201	10	X	X	2
15-204	12	X	X	2
15-205	4	X	X	4

# 38999 INSERT ARRANGEMENTS

MIL-DTL-38999 AVAILABLE INSERT ARRANGEMENTS					
ARRANGEMENT	SERVICE RATING	CONTACT SIZE (AWG)			
		22D	20	16	12
A35	M	6	X	X	X
A98	I	X	3	X	X
B2	I	X	X	2	X
B4	I	X	4	X	X
B5	I	X	5	X	X
B35	M	13	X	X	X
B98	I	X	6	X	X
B99	I	X	7	X	X
C4	I	X	X	4	X
C8	I	X	8	X	X
C35	M	22	X	X	X
C98	I	X	10	X	X
D5	II	X	X	5	X
D15	I	X	14	1	X
D18	I	X	18	X	X
D19	I	X	19	X	X
D35	M	37	X	X	X
D97	I	X	8	4	X
E6	I	X	X	X	6
E8	II	X	X	8	X
E26	I	X	26	X	X
E35	M	55	X	X	X
E99	I	X	21	2	X
F11	II	X	X	11	X
F28	I	X	26	2	X
F30	I	X	29	1	X
F32	I	X	32	X	X

MIL-DTL-38999 AVAILABLE INSERT ARRANGEMENTS					
ARRANGEMENT	SERVICE RATING	CONTACT SIZE (AWG)			
		22D	20	16	12
F35	M	66			
F45	M	67	X	X	X
G11	I	X	X	X	11
G16	II	X	X	16	X
G24	I	X	24	X	X
G25	I	X	25	X	X
G27	I	X	27	X	X
G35	M	79	X	X	X
G39	I	X	37	2	X
G41	I	X	41	X	X
H21	II	X	X	21	X
H32	I	X	32	X	X
H34	I	X	34	X	X
H35	M	100	X	X	X
H36	I	X	36	X	X
H53	I	X	53	X	X
H55	I	X	55	X	X
H97	I	X	X	16	X
H99	II	X	X	11	X
J4	I	X	48	8	X
J19	I	X	X	X	19
J24	I	X	X	12	12
J29	I	X	X	29	X
J35	M	128	X	X	X
J43	I	X	23	20	X
J61	I	X	61	X	X

# 26482 INSERT ARRANGEMENTS

MIL-DTL-26482 AVAILABLE INSERT ARRANGEMENTS				
INSERT ARRANGEMENT	CONTACT SIZE (AWG)			SERVICE RATING
	20	16	12	
8-2	2	X	X	I
8-3	3	X	X	I
8-4	4	X	X	I
8-33	3	X	X	I
8-98	3	X	X	I
10-6	6	X	X	I
10-7	7	X	X	I
12-3	X	3	X	II
12-8	8	X	X	I
12-10	10	X	X	I
14-2	X	X	2	I
14-4	X	X	4	I
14-5	X	5	X	II
14-9	5	X	4	I
14-12	8	4	X	I
14-15	14	1	X	I
14-18	18	X	X	I
14-19	19	X	X	I
16-8	X	8	X	II
16-14	8	X	6	I
16-23	22	1	X	I
16-26	26	X	X	I
18-8	X	X	8	I
18-11	X	11	X	II
18-30	29	1	X	I
18-32	32	X	X	I
20-16	X	16	X	II
20-24	24	X	X	I
20-39	37	2	X	I
20-41	41	X	X	I
22-12	X	X	12	I
22-21	X	21	X	II
22-41	27	14	X	I
22-55	55	X	X	I
24-19	X	X	19	II
24-31	X	31	X	I
24-61	61	X	X	I

# 5015 INSERT ARRANGEMENTS

MIL-C-5015 AVAILABLE INSERT ARRANGEMENTS			
ARRANGEMENT	NUMBER OF CONTACTS	CONTACT SIZE	SERVICE RATING
12S-4	1	16	D
12-5	1	12	D
14-3	1	8	A
14S-4	1	16	D
16-12	1	4	A
20-2	1	0	D
22-7	1	0	E
10SL-4	2	16	A
12S-3	2	16	A
14S-9	2	16	A
16S-4	2	16	D
16-11	2	12	A
18-3	2	12	D
20-23	2	8	A
22-1	2	8	D
22-8	2	12	E
24-9	2	4	A
32-5	2	0	D
10SL-3	3	16	A
14S-1	3	16	A
16S-5	3	16	A
16-10	3	12	A
18-21	3	12	A
18-22	3	16	D
20-23	3	12	D
20-19	3	8	A
22-2	3	8	D
28-3	3	8	E
28-6	3	4	D
36-4	3	0	D(A) A(B,C)
12SA10	4	16	INST
14S-2	4	16	INST
16-9	4	1-16, 2-12	A
18-4	4	16	D
18-10	4	12	A
20-4	4	12	D
20-24	4	2-16, 2-8	A

MIL-C-5015 AVAILABLE INSERT ARRANGEMENTS			
ARRANGEMENT	NUMBER OF CONTACTS	CONTACT SIZE	SERVICE RATING
22-22	4	8	A
24-22	4	8	D
32-17	4	4	D
26-5	4	0	A
14S-5	5	16	INST
16S-8	5	16	A
18-11	5	12	A
18-20	5	16	A
24-2	7	12	D
24-10	7	8	A
28-10	7	3-12, 2-8, 2-4	D(G) A(A, B, C, D, E, F)
36-77	7	4	D
18-8	8	7-16, 1-12	A
20-7	8	16	D(A, B, G, H) A(All Others)
22-18	8	16	D(All Others) A(C, D, 3)
22-23	8	12	D(H) A(All Others)
24-6	8	12	D(A, G, H) A(All Others)
32-15	8	6-12, 2-0	D
20-16	9	7-16, 2-12	A
20-18	9	6-16, 3-12	A
22-20	9	16	A
24-11	9	6-12, 3-8	A
28A16	9	5-16, 4-4	A(E) INST(All Others)
32-3	9	4-16, 2-12, 2-4, 1-0	D
14SA10	10	20	INST
18-1	10	16	A(B, C, F, G) INST(All Others)
18-19	10	16	A
28-19	10	6-16, 4-12	D(A, B) B(H, M) A(All Others)
20-31	11	16	A
20-33	11	16	A
24-20	11	9-16, 2-12	D
28-14	11	16	D
24B24	12	12	A
28-9	12	6-16, 6-12	D
28-51	12	12	D
20-11	13	16	INST
20-27	14	16	A
22-19	14	16	A
28-2	14	12-16, 2-12	D
28-20	14	4-16, 10-12	A
36-78	14	2-16, 12-8	D
28-17	15	16	B(R) D(M, N, P) A(All Others)
24-5	16	16	A
24-7	16	14-16, 2-12	A
20-29	17	16	A

**MIL-C-5015 AVAILABLE INSERT ARRANGEMENTS**

<b>ARRANGEMENT</b>	<b>NUMBER OF CONTACTS</b>	<b>CONTACT SIZE</b>	<b>SERVICE RATING</b>
22-14	19	16	A
28-16	20	16	A
28-11	22	18-16, 4-12	A
26-1	22	18-16, 4-12	D
32-6	23	16-16, 2-12, 3-8, 2-4	A
20A24	24	20	INST
24-28	24	16	INST
28-12	26	16	A
224A28	28	16	INST
32-8	30	24-16, 6-12	A
36-9	31	14-16, 14-12, 2-8, 1-4	A
28-15	35	16	A
32-7	35	28-16, 7-12	A(All Others) INST(A, B, H, J)
27-21	37	16	A
28A51	43	16	A
32-73	46	16	A
36-8	47	46-16, 1-12	A
336-10	48	16	A
36-52	52	16	A
32A10 & 32-22	54	16	A
28-72	57	20	INST
40-56	85	16	A
32-101	101	20	INST